

# T1 STROBE-DMX



Channel	Channel Name	DMX	Function
13CH			
1	dimmer	0-255	0-100%
2	dimmer 16bit	0-255	0-100%
3	strobe	0-3	off
		4-7	on
		8-76	synchronized strobe, slow to fast
		77-145	pulse strobe, slow to fast
		146-215	random strobe, slow to fast
		216-255	on
4	R	0-255	0-100%
5	G	0-255	0-100%
6	B	0-255	0-100%
7	color	0	无功能
		1-2	2700K(R=156, G=118, B=0, W=63)
		3-4	3200K(R=156, G=141, B=5, W=89)
		5-6	4200K(R=156, G=141, B=14, W=255)
		7-8	5600K(R=156, G=207, B=54, W=255)
		9-10	8000K(R=130, G=255, B=96, W=255)
		11	Blue (R=0, G=0, B=255, W=0)
		12-48	R=0, G+, B=255, W=0
		49	Cyan (R=0, G=255, B=255, W=0)
		50-86	R=0, G=255, B-, W=0
		87	Green (R=0, G=255, B=0, W=0)
		88-124	R+, G=255, B=0, W=0
		125	Yellow (R=255, G=255, B=0, W=0)
		126-162	R=255, G-, B=0, W=0
		163	Red (R=255, G=0, B=0, W=0)
		164-200	R=255, G=0, B+, W=0
		201	Magenta (R=255, G=0, B=255, W=0)
		202-238	R-, G=0, B=255, W=0
		239	Blue (R=0, G=0, B=255, W=0)
		240-247	Color fade, fast to slow
248-255	Color jump, fast to slow		
8	pattern	0-4	no function
		5-9	pattern 1
		10-14	pattern 2
		15-19	pattern 3
		20-24	pattern 4
		25-29	pattern 5
		30-34	pattern 6

# T1 STROBE-DMX



Channel	Channel Name	DMX	Function
8	pattern	35-39	pattern 7
		40-44	pattern 8
		45-49	pattern 9
		50-54	pattern 10
		55-59	pattern 11
		60-64	pattern 12
		65-69	pattern 13
		70-74	pattern 14
		75-255	no function
9	LED built-in	0-15	no function
		16-20	LED built-in 1
		21-25	LED built-in 2
		26-30	LED built-in 3
		31-35	LED built-in 4
		36-40	LED built-in 5
		41-45	LED built-in 6
		46-50	LED built-in 7
		51-55	LED built-in 8
		56-60	LED built-in 9
		61-65	LED built-in 10
		66-70	LED built-in 11
		71-135	LED built-in 12 (main built-in)
		136-140	LED built-in 13
		141-145	LED built-in 14
		146-150	LED built-in 15
		151-155	LED built-in 16
		156-160	LED built-in 17
		161-165	LED built-in 18
		166-170	LED built-in 19
171-175	LED built-in 20		
176-180	LED built-in 21		
181-185	LED built-in 22		
186-190	LED built-in 23		
191-255	LED built-in 24 (main built-in)		
10	LED built-in speed	0-127	fast to slow
		128	stop
		129-255	reverse slow to fast
11	LED built-in delay	0-255	fast to slow
12	background color	0	无功能

# T1 STROBE-DMX



Channel	Channel Name	DMX	Function
13CH			
12	background color	1-2	2700K(R=156, G=118, B=0, W=63)
		3-4	3200K(R=156, G=141, B=5, W=89)
		5-6	4200K(R=156, G=141, B=14, W=255)
		7-8	5600K(R=156, G=207, B=54, W=255)
		9-10	8000K(R=130, G=255, B=96, W=255)
		11	Blue (R=0, G=0, B=255, W=0)
		12-48	R=0, G+, B=255, W=0
		49	Cyan (R=0, G=255, B=255, W=0)
		50-86	R=0, G=255, B-, W=0
		87	Green (R=0, G=255, B=0, W=0)
		88-124	R+, G=255, B=0, W=0
		125	Yellow (R=255, G=255, B=0, W=0)
		126-162	R=255, G-, B=0, W=0
		163	Red (R=255, G=0, B=0, W=0)
		164-200	R=255, G=0, B+, W=0
		201	Magenta (R=255, G=0, B=255, W=0)
		202-238	R-, G=0, B=255, W=0
		239	Blue (R=0, G=0, B=255, W=0)
240-247	Color fade, fast to slow		
248-255	Color jump, fast to slow		
13	background color dimmer	0-255	0-100%